

# ZLog 6 Serial Protocol

Command Format
<cmd>[=<value>]<CR>
if =<value> is specified, then set the value. if =<value> is not specified, then get the value.
<CR> = 0x0D

## Commands

System (immediate execution on character receive)		Z6M/D/R
!	Invoke Loader	M D R
*	Reset	M D R
Q	Repeat Last Command	M D R
<	Toggle Logging Output	M D R

Debug		Z6M/D/R
DB	Debug (0=off, 1=on)	M D R
CD	Coefficient Dump	M D R
DD	Dump Calc Data	M D R
CL	Calibrate	-
ED	Dump EEPROM (4 pages) n = pagenum	R
ET	EEPROM Test	R
EI	EEPROM ID	R
EE	Erase EEPROM (chip erase)	R
E1	Erase EEPROM Page 1	R
PW	Show Pulse Width (trigger)	R
DT	Data Test	R
DR	Data Recovery	R

BR	Baud Rate	-
----	-----------	---

General		Z6M/D/R
SV	Show Version	M D R
CF	Enter Config Menu	D R
CR	Config Reset Defaults	D R
CW	Config Write (after making changes)	D R

Measurements		Z6M/D/R
AL	Display the Altitude	M D R
TC	Display the Temperature in Celsius	M D R
TF	Display the Temperature in Fahrenheit	M D R
PR	Display the Pressure (millibar)	M D R
CB	Altitude Calibration (pascals or millibar*100) example: CB=101325	-
CI	Altitude Calibration (inches Hg * 100) example: CI=2992	-

Display		Z6M/D/R
ZR	Zero 0 = off (absolute mode) 1 = on (relative mode)	M D R
MX	Show Max Altitude	M D R
MC	Max Altitude Clear	M D R

Auto Functions		Z6M/D/R
AZ	Auto Zero 0 = off 1 = trigger 2 = powerup 3 = record	D R
AS	Auto Start Record 0 = off 1 = time 2 = altitude 3 = trigger	R
ST	Start Time n = seconds	R
SA	Start Altitude n = feet / yards / meters	R
AP	Auto Stop 0 = off 1 = time 2 = altitude	R
PT	Stop Time n = seconds	R
PA	Stop Altitude n = feet / yards / meters	R
UA	Units Altitude 0 = feet 1 = yards 2 = meters	-
UP	Units Pressure 0 = millibars 1 = inHg	-

<b>Recording</b>		<b>Z6M/D/R</b>
SR	Sampling Rate n = sampling rate (in intervals)	R
SI	Sampling Interval (msec)	R
RT	Record Trigger 0 = off 1 = on	R
RV	Reverse Trigger 0 = off 1 = on	D R
RC	Recording 0 = off 1 = on	R

<b>Data</b>		<b>Z6M/D/R</b>
LS	List Data Sets	R
NS	Get Number of Sets	R
DL	Download Set(s) 0 = all sets n = set #n	R
EA	Erase All Data Sets 1 = erase all n = no erase	R
ES	Erase Set(s) n = set #n	R